



*Kevin Technologies Pvt. Ltd*

201, Shapath - I, Opp.Rajpath Club, S.G.Road, Bodakdev,  
Ahmedabad - 380015

Phone: 079-26872555 / 26870556

Fax: 079-26878930

## Digital RPM Indicators (4DRPM)

### Product Description / Features

<b>Input</b>  (Any One can be selected)	<b>Analog Inputs</b> [4-20 mA / 0-20 mA linear] [0-5 V DC / 0-10 V DC]  (Factory set for 0 to 9999) Programmable  <b>Digital Pulse Input (Proximity Input)</b>
<b>Range Selection</b>	Range Selection = Programmable  [50, 100, 125, 200, 250, 400, 800, 1000, 2000 , 4000, 8000 RPM]
<b>Display</b>	4-Digit Seven Segment LED Display
<b>Decimal Point</b>	Selection & Programmable
<b>Offset Value</b>	Programmable (+0-5000 count).
<b>Zero Data</b>	Programmable (-0-60 count).
<b>Mounting</b>	Flush Panel
<b>Case Size</b>	48 (H) X 96 (W) X 110 (D) mm, Cut Out: 46 (H) X 92 (W)
<b>Operating supply</b>	230 V AC, 50 Hz
<b>Operating Current</b>	500 mA Max.
<b>Accessories</b>	Operational Manual & Mounting clamps